

## Style A NEMA Steel Adjustable Motor Bases

FRAME & PART NO.	AL	АМ	AX	ВВ	E	F	АО	AR	AU	вт	AT	XC	D BOLT	AY BOLT	APPROX WT. (LBS)
48	10	6-1/4	1-1/8	4-1/4	2-1/8	1-3/8	3-1/2	2-3/4	3/8	3	.078	7/8	5/16X1	3/8X4	3
56	10-5/8	6-1/2	1-1/8	4-1/2	2-7/16	1-1/2	3-13/16	2-7/8	3/8	3	.078	7/8	5/16X1	3/8X4	3
143*	10-1/2	7-1/2	1-1/8	5-1/2	2-3/4	2	3-3/4	3-3/8	3/8	3	.119	13/16	5/16X1	3/8X4	5
145*	10-1/2	8-1/2	1-1/8	6-1/2	2-3/4	2-1/2	3-3/4	3-7/8	3/8	3	.119	13/16	5/16X1	3/8X4	6
182*	12-3/4	9-1/2	1-1/2	6-1/2	3-3/4	2-1/4	4-1/2	4/1/4	1/2	3	.134	1-1/2	3/8X1-3/4	1/2X6	9
184*	12-3/4	10-1/2	1-1/2	7-1/2	3-3/4	2-3/4	4-1/2	4-3/4	1/2	3	.134	1-1/2	3/8X1-3/4	1/2X6	10
213*	15	11	1-3/4	7-1/2	4-1/4	2-3/4	5-1/4	4-3/4	1/2	3-1/2	.164	1-1/2	3/8X1-3/4	1/2X6	14
215*	15	12-1/2	1-3/4	9	4-1/4	3-1/2	5-1/4	5-1/2	1/2	3-1/2	.164	1-1/2	3/8X1-3/4	1/2X6	16

Bases Noted (\*) also available in standard stock double adjusting style A2. Adjusting bolts on style A2 bases are in line with D bolts on F dimension.

Dimensions are in inches: Bases are furnished with one coat of epoxy powdercoat gray paint and zinc plated nuts and bolts. Bases listed may also be used if the motor frame is suceeded by S, T, U, US or any letter combination as long as the motor complies with NEMA.

The liability of the Overly Hautz Company to the purchaser is limited to replacement of defective materials supplied. One year from the date of our shipment all liability shall terminate. There are no warranties which extend beyond the description on the face herof.

## Pan Bases for Smaller Motors - Style A & A2

The industry standard base for smaller motors ranging from large fractionals to approximately 20 horsepower. Features a one-piece formed base plate and single or double bolt adjustment with push-pull action.

